

SFH ONT 612A STATUS AND MAINTENANCE JULY 2016			
LED	NORMAL	IF ...	THEN ...
POWER	GREEN	OFF	CHECK POWER SUPPLY
		FLASHING	ON BATTERY
BATTERY	GREEN	OFF	BATTERY LOW OR MISSING
FAIL	OFF	RED	DIAGNOSTIC TEST FAILURE
		FLASHING	PASSED TEST, NOT COMMUNICATING
VIDEO	OFF	RED	SERVICE PROVISIONED BUT
			VIDEO POWER TOO LOW
NETWORK	GREEN	OFF	NO OPTICAL LINK ESTABLISHED
OMI	GREEN	OFF	OMI CHANNEL NOT AVAILABLE
POTS	OFF	GREEN	ONE OR MORE PHONES HOOK
			RINGING OR UNDER TEST
ETHERNET	GREEN	GREEN	100MBPS ENABLED (BLINKING Wdata activity)
	AMBER	AMBER	100MBPS ENABLED (BLINKING Wdata activity)
	or	RED	NO LINK DETECTED
	OFF	OFF	ETHERNET DISABLED
MoCA	GREEN	GREEN	ABOVE MoCA TARGET RATE (BLINKING Wdata activity)
	AMBER	AMBER	BELOW MoCA TARGET RATE (BLINKING Wdata activity)
	or	RED	MoCA NETWORK NOT ESTABLISHED
	OFF	OFF	MoCA DISABLED